



CONVENIENCE



# **Colour wireless LED** 4-in-1 printer

MFC-L3745CDW











## **Colour wireless LED 4-in-1 printer**

The feature rich MFC-L3745CDW offers full colour prints with fastest in its class print speeds of up to 22 pages<sup>6</sup> per minute. With both wired and wireless connectivity, and the ability to print straight from your mobile, this machine can support the busiest of offices. The 9.3cm colour touchscreen will allow you to access your favourite features quickly and easily.

### MFC-L3745CDW



### **Key Features:**

- Fast print speeds of up to 22 pages<sup>6</sup> per minute
- Large paper capacity of 250 sheets
- Automatic 2-sided (duplex) printing
- 50 sheet Auto Document Feeder (ADF)
- Easy to use 9.3cm colour touchscreen
- Wired and wireless connectivity
- Print from or scan directly to a USB stick
- Up to 1,000 pages<sup>1</sup> in-box toners



### Productivity gains for your business

Watch your business productivity soar with up to 22PPM print speeds<sup>8</sup> and the time-saving 50 sheet ADF - scanning or copying documents has never been easier.



## Wireless, mobile and cloud connectivity

Loads of connectivity options for your business. Print wirelessly from your desktop, laptop, smartphone or tablet for mobile device printing and scanning.



## Best value - get business features at low running costs

With high-yield toners available (up to 2,500 pages¹ BK and 2,300 pages¹ CMY), your business can now benefit from super low running costs with high quality 2400dpi printing and bundled with industry leading Nuance document software, ensuring you get maximum value from an economical multi-function device.



### Designed to go the distance

Built to perform for longer, the MFC-L3745CDW has been designed with you in mind. Made from robust and hard wearing materials and supported by outstanding service as standard, Brother's award winning<sup>9</sup> reliability allows you to deliver uncompromised performance at all times.

General	
Technology	Electrophotographic LED
Processor	Cortex-A9 800MHz Sub: ARM946 133MHz
Wired Network	Ethernet 10Base-T/100Base-TX
Wireless Network	IEEE 802.11b/g/n
Control Panel	9.3cm colour touchscreen
Memory	512MB
Local Interface	Hi-Speed USB 2.0
Mobile Print	Print from your mobile devices to your Brother printer
Print	
Print Speed (A4)	Up to 22PPM Colour & Monochrome
Print Speed 2-sided (duplex) (A4)	Up to 8 sides per minute Colour & Monochrome - print on to both sides of the paper automatically
Resolution	2,400 dpi (600 x 2400)
Quiet Mode	A mode to reduce the printing noise by reducing the print speed
FPOT (First Print Out Time)	Less than 14 seconds from ready mode
Warm Up Time	Less than 24 seconds from sleep mode
Print Languages	PCL6, BR-Script3 PDF Version 1.7, XPS Version 1.0
Embedded Fonts (PCL)	73 scalable fonts, 12 bitmap fonts

Embedded Fonts (Postscript)	66 scalable fonts
Embedded Barcodes (PCL)	*Code39, Interleaved 2 of 5, FIM (US-PostNet) Post Net (US-PostNet) EAN-8, EAN-13, UPC-A, UPC-E, Codabar ISBN (EAN) ISBN (UPC-E) Code128 (set A, set B, set C) EAN128 (set A, set B, set C) Code93 GS1Databar MSI
Printer Functions	
N-up Printing <sup>3</sup>	Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)
Poster Printing <sup>4</sup>	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages
Watermark Printing⁴	Watermark your documents with predefined text or with your own user-defined messages
ID Printing⁴	Add identification to your printed documents (date & time, short custom message or PC username)
Manual 2-sided (duplex) Print <sup>4</sup>	Manual 2-sided (duplex) printing (recommended for media not supported by automatic 2-sided (duplex) print)
Booklet Printing <sup>4</sup>	Print documents in A5 booklet format using automatic or manual 2-sided (duplex) print
Print Profiles³	Store your favourite driver settings as profiles to easily recall them
Print Text In Black <sup>4</sup>	Converts all text in your documents to black when printed
Print from USB	Print directly from a USB flash drive (PDFv1.7, JPEG, TIFF)
Configurable Shortcuts	Create up to 18 personalised shortcuts for a quick and easy access to your regularly print, copy, scan and fax functions

Printer Drivers		Grey Scale	256 shades of grey (8 bit)
Windows <sup>®</sup>	Windows® 10 (32 & 64 bit editions), Windows® 8 (32	Receipt Copying	Produces clearer copies of receipts
Windo Windo	& 64 bit editions), Windows® 7 (32 & 64 bit editions), Windows® Server 2016 (32 & 64 bit editions)*, Windows® Server 2012, 2012R2 & 2008R2*, Windows® Server 2008 (32 & 64 bit editions)*	Enlarge Text Copy <sup>8</sup>	Makes reading copied documents easier if the size of the text on the original document is small
Macintosh <sup>5</sup>	macOS v10.11.6, 10.12.x, 10.13.x		
Linux <sup>5</sup>	CUPS, LPD/LPRng (32 & 64 bit editions)	Scan	
PostScript Universal Printer Driver <sup>5</sup>	Driver for Windows® that enables you to print to any	Scanner Type	CIS (Contact Image Sensor)
	network or locally-connected Brother laser printer that supports PostScript	Colour & Monochrome Scanning	Yes
PCI Driver <sup>5</sup>	Generic PCL XL driver	Scan Speed Monochrome	27ipm (images per minute)
	30.0.10 1 02 12 3.110	Scan Speed Colour	21ipm (images per minute)
Paper Handling		Scan Resolution from Scanner Glass	Up to 1,200 x 2,400dpi
Paper Input	Standard Tray - 250 sheets	Interpolated Scan Resolution	Up to 19,200 x 19,200dpi
	ADF - 50 Sheets Manual feed slot - 1 sheet	Scan Resolution from ADF	Up to 600 x 600dpi
Paper Output	150 sheets Face Down (80g/m2) 1 sheet face-up (straight paper path)	Colour Depth	48 bit colour Processing (Input) 24 bit colour Processing (Output)
Media Type & Weights Standard Tray	Plain & Recycled paper (between 60 - 163g/m2)	Grey Scale	16bit colour Processing (Input) 8bit colour Processing (Output)
Media Sizes Standard Tray	A4, Letter, A5, A5 (Long Edge), A6, Executive		- O(
Media Type & Weights ADF	Plain & Recycled paper (between 60 - 105g/m2)		
Media Sizes ADF	Width 105 to 218 mm, Length 148 to 357.6 mm	Scanner Functions	
Media Type & Weights Manual feed	Plain, Recycled, Bond, Label, Envelope paper	Scan to E-mail	Scan and share documents via e-mail client
slot Media Sizes Manual feed slot	(between 60 - 163g/m2) Width 76.2 to 216 mm	Scan to OCR	Scan documents directly into your word processing application for instant editing
	Length 116 to 355.6 mm Envelope; COM-10, DL, C5, Monarch	Scan to Image	Scan into your preffered image editing software
Envelope & Label Printing	Yes, from the manual feed slot: support for 1	Scan to File	Scan to a file on your computer
	envelope / sheet	Scan to USB	Scan directly to a USB flash drive
		Scan to Network Folder	Scan documents to a nominated folder on your network without using a Windows PC
Mobile and Web		Scan to FTP	Scan documents directly to a FTP server
Connectivity	District and the second forms are sized forms	Scan Profile3	Create up to 25 preset network, FTP profiles for an easy way to store multiple scan settings
Brother iPrint&Scan (Android)	Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an Android device	Scan to Sharepoint (Local infrastructure only)	Scan documents directly into SharePoint
Brother iPrint&Scan	Print from, scan to, send faxes, preview received faxes,	Scan to Searchable PDF	Scan documents to searchable PDF files
(iPad / iPhone / iPod)	preview copies and check the machine status from an iPad / iPhone / iPod Touch	Auto Deskew	Yes
Brother iPrint&Scan (Windows® Phone)	Print from and scan to a smart phone running the Windows® Phone Operating System	Base Colour Removal  ID Scan	Yes Yes
Brother Print&Scan (Windows® 8,10 & RT)	Print from and scan to a Windows® 8,10 or Windows RT Tablet	1 to 2 Scan	Yes
Apple AirPrint	Print from and scan to most common file types from any AirPrint enabled application	Scanner Drivers	
Brother Print Service Plugin	Print from Android devices without a dedicated App	Windows®	TWAIN & WIA Windows® 10 (32 & 64 bit editions), Windows® 8 (32 & 64 bit editions), Windows® 7 (32 &
Mopria	Print most common file types from Mopria supported Android devices	Macintosh⁵	64 bit editions) TWAIN
Brother Apps <sup>8</sup>	Print creative center, Scan to Mobile, Scan to Searchable PDF, Enlarge Text Copy, Fax forward to	Macilitosii	macOS v10.11.6, 10.12.x, 10.13.x
	Cloud/E-mail, Scan to PowerPoint, Scan to Excel, Scan to Word, Easy scan to E-mail	Linux <sup>5</sup>	SANE (32 & 64 bit editions)
Web Connect <sup>8</sup>	Print from and scan to without using a PC on Box,	Fax	
Dropbox, Eve OneNote	Dropbox, Evernote, OneDrive, Google DriveTM OneNote	Fax Modem	33,600bps (Super G3)
		PC Fax Send3&8 and Receive <sup>4&amp;8</sup>	Send and Receive faxes directly from your PC
Сору		2-sided (duplex) Fax Receive	Yes
Print Speed (A4)	Up to 24CPM <sup>10</sup> Colour & Monochrome	Memory Transmission	Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)
FCOT (First Copy Time Out)	Less than 15 seconds from ready mode Colour & Monochrome	Out of Paper Reception	Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)
Resolution	Up to 600 x 600dpi	Error Correction Mode (ECM)	The MFC will detect line errors during fax transmission
Multi-Copying/Stack/Sort	Makes up to 99 copies of each page / Stacks or Sorts		and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)
Enlargement/Reduction Ratio	Reduce or increase document sizes from 25% to 400% in 1% increments	Auto Reduction	When receiving a single page document longer than (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet
N in 1 Copying	Allows the user to compress 2 or 4 pages on to a	Broadcasting	Send the same fax message up to 250 locations
2in1 ID Convins	single A4 sheet	Grey Scale	256 shades (8 bit) of grey are available for faxing
2in1 ID Copying	Allows the user to copy both sides of an ID card to a single A4 sheet	diey doale	200 shades to bit, of grey are available for laxify

Fleet Management Tools	
Unattended Installer <sup>4</sup>	Ability to centrally deploy and customise our drivers and software
MSI Installer <sup>4</sup>	Modular installers that can be distributed through Active Directory®
BRAdmin Light <sup>485</sup>	LAN/WAN management software
Embedded Web Server	Web based print management software embedded onto the device
Driver Deployment Wizard <sup>485</sup>	Easily create print drivers for hassle free deployment over your network
Software	
Brother iPrint&Scan (Windows & Mac) <sup>5</sup>	Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from windows or macOS PC
Nuance® PaperPort 14 SE <sup>5</sup>	Document management & sharing program
Network and Security	
Wired Network	Ethernet 10Base-T/100Base-TX
Wired Network Security	APOP, POP before SMTP, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP- TTLS), Kerberos
Wireless Network	IEEE 802.11b/g/n (Infrastructure Mode) IEEE 802.11g/n (Wi-Fi Direct)
Wireless Network Security	WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES)  "WI-Fi Direct supports WPA2-PSK (AES) only.APOP, POP before SMTP, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP), SNMP v3 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos
Wireless Setup Support	Wi-Fi Protected Setup (WPS)
Wireless Applications	Vertical Pairing
Wi-Fi Direct™	Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)
IPv4	ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/ NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/IPPS, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server,

TFTP client and server, ICMP, Web Services

(Print/Scan), SNTP Client

IPv6 NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS,

SMTP Client, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, SNTP Client, Web Services (Print/Scan)

IP Filter Restrict which network users can or cannot access the device over the network (IPv4 only)

Secure Print Protect print jobs with a 4 digit release code required at

the device in order for them to be printed

Setting Lock Secures access to the devices control panel by

locking it

Secure Function Lock 3.0 Restrict access to individual or groups of users over a

network. Can be used with PC User Login Names for up to 100 users

E-mail Notifications Automatically have the device send e-mail alerts when

it requires attention, such as when the toner is low or

needs replacing

E-mail Reports Receive usage reports on a regular basis via e-mail

#### **Supplies and Accessories**

Up to 1,000 pages1 C/M/Y/BK In-box Toner Standard-Yield Toner Up to 1,300 pages1 C/M/Y (TN-253) Up to 2,500 pages<sup>1</sup> BK (TN-253) High-Yield Toner Up to 2,300 pages1 C/M/Y (TN-257) Drum Unit Up to 18,000 pages1 (1 page / job) (DR-253CL)

Dimensions and Weights	

Without Carton (WXDXH)	410 x 4/5 x 414 mm -23.4kg
With Carton (WxDxH)	589 x 523 x 568 mm - 27.6kg

#### **Duty Cycles**

Recommended Monthly 300 to 1.500 pages<sup>9</sup> monthly print volume

#### **Environment**

**Power Consumption** Printing - 430W, Ready - 75W, Quiet Mode - 260W, Sleep - 10.1W, Deep Sleep - 1.2W, Off - 0.04W

Sound Pressure Level Printing - 47dB(A) Ready - 33dB(A)

Quiet Mode - 43dB(A)

Printing - 6.11B(A) Monochrome / 6.16B(A) Sound Power Colour Ready - 4.67B(A), Quiet Mode - 5.71B(A)

Monochrome / 5.73B(A) Colour, Deep Sleep - Inaudible Power Saving This enables the printer to consume less energy when

Toner Save Mode This reduces the toner usage and helps to reduce the total cost of printer ownership

Eco Mode

- 1 Approx declared yield value in accordance with ISO/IEC 19798.
- 2 Calculated with 80g/m<sup>2</sup> paper.
- 3 Windows® & Mac® only. 4 Windows® only.
- 5 Optional download
- 6 ISO print speed based on ISO/IEC 24734 (after first set of ISO test pages).
- 7 Requires Brother Software.
- 8 ISO copy speed is based on ISO/IEC 24735.
- 9 The recommended range of monthly printed pages to achieve the best possible performance and printer life. Printers are intended to handle occasional usage beyond the range with little or no effect. Consistently printing above the recommended print volume, however, may adversely affect the print quality or life of the machine. It is always best to choose a printer with an appropriate recommended print volume to allow for any anticipated increase in printing needs.
- \* Windows® Server supports network printing only

All specifications correct at time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.







### Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call Brother this approach Brother Earth.

www.brotherearth.com



youtube.com/user/BrotherAU/videos

Earth



